Tripp Lite
1111 West 35th Street
Chicago, IL 60609 USA
Telephone: +(773) 869 1234
E-mail: saleshelp@tripplite.com

Model #: B006-VUA4-K-R

KVM Switch - 4-Port KVM Switch with Audio, OSD and Peripheral Sharing

Highlights

- Control up to 4 USB or PS/2 computers from a single VGA monitor and USB or PS/2 keyboard/mouse
- Package includes 4 USB KVM cable kits
- Includes a built-in 2-Port USB 2.0 hub for sharing of devices amongst computers connected with a USB KVM cable kit
- Built-in 3.5mm audio jacks allow speaker and microphone audio to be shared amongst the connected computers
- Switch between connected computers via pushbuttons, hotkey commands, OSD or mouse switching function
- 2-Level security - 1 Administrator and up to 4 Users
- Includes rackmount hardware for mounting in a 19in rack
- Compatible with Windows, Mac, Linux, Sun, UNIX, Novell and DOS
- 1 Year Limited Warranty

Description

Tripp Lite's B006-VUA4-K-R is the optimal solution for controlling multiple computers, audio and USB peripherals, and can be used in either a desktop environment or mounted in a 19in rack. Connect up to 4 USB computers with the included 4 USB KVM cable kits, or use P757-010 PS/2 KVM cable kits to connect PS/2 computers. Built-in 3.5mm jacks allow for speaker and microphone audio to be shared amongst the connected computers. Also built-in is a 2-Port USB 2.0 hub, which allows for the sharing of USB devices amongst computers connected via USB KVM cable kits. KVM console, Audio and USB can be switched independently of each other - Control one computer while listening to audio from a second computer and printing to a USB printer from a third. Switch the focus of KVM, Audio and USB functionality using pushbuttons, OSD, hotkey commands, auto scan mode or the mouse switching function. The mouse switching function allows focus to be switched between ports by double-clicking the scroll button on a scroll mouse. The on-screen display (OSD) provides two levels of security, with 1 Administrator account and up to 4 User accounts, and can be displayed in English, Japanese or German. It supports video resolutions up to 2048 x 1536, and features a compact design that does not require software or complicated set-up procedures. Compatible with Windows, Mac, Linux, Sun, UNIX, Novell and DOS.

Applications

- Small Office/Home Office (SOHO). Control multiple computers, audio and USB peripherals, and use in either a desktop environment or mount in a 19in rack.

Package Includes

- B006-VUA4-K-R KVM switch
- (4) USB KVM cable kits
- PS/2 to USB adapter cable
- Firmware upgrade cable
- 19in rackmount hardware
- External Power Supply (Input: 100-240V, 0.5A, 50/60Hz Output: 5.3V, 2.4A)
- Owner's Manual

Features

- Control up to 4 computers from a single VGA monitor and USB or PS/2 keyboard/mouse
- Package includes two 4ft and two 6ft USB KVM cable kits. P756-010 10ft USB KVM cable kits are availabe separately if a longer distance is required.
- P757-010 PS/2 KVM cable kits are available to connect PS/2 computers.
- Built-in 2-Port USB 2.0 hub allows USB peripherals to be shared amongst computers connected via USB KVM cable kits
- Built-in 3.5mm jacks allow for speaker and microphone audio to be shared amongst the connected computers
- KVM console, Audio and USB can be switched independently of each other - Control one computer while listening to audio from a second computer and printing to a USB printer from a third
- Switch the focus of KVM, Audio and USB functionality using pushbuttons, OSD, hotkey commands, auto scan mode or the mouse switching function
- The mouse switching function allows focus to be switched between ports by double-clicking the scroll button on a scroll mouse
- Automatically monitor connected computers via Auto Scan Mode
- The on-screen display (OSD) provides two levels of security, with 1 Administrator account and up to 4 User accounts, and can be displayed in English, Japanese or German
- Comes with rackmount hardware that allows for mounting in a 19in rack
- Comes with a USB to (x2) PS/2 adapter, which allows you to use either USB or PS/2 keyboard and mice to control the connected computers
- Additional console audio jacks are conveniently located on the front panel of the KVM switch, making them ideal for use with IP phones
- Supports hot plugging – computers and devices can be unplugged and plugged in without having to shut down the KVM switch
- Supports video resolutions up to 2048 x 1536, DDC2B
- No software or complicated set-up procedures required
- The KVM switch stores the monitor's EDID (Extended Display Identification Data) to optimize display resolution
- Compatible with Windows, Mac, Linux, Sun, UNIX, Novell and DOS
- 1 Year Limited Warranty

Specifications

OVERVIEW	
# Of Users	1
Port Control	Push Buttons, Hotkeys, OSD Mouse Switching
Max CPU	4
IP Remote Access	NO
PHYSICAL	
Shipping weight (lbs)	4.9
Unit Dimensions (HWD/in)	1.6 x 7.9 x 2.75
Shipping Dimensions (HWD/in)	3.9 x 11.1 x 6.8
Unit weight (lbs)	1.75
Style	Desktop/1U Rackmount
CONNECTIONS	
Ports	4
Other Ports	(x2) USB
Computer/Server Ports - Port 1	(x4) HD17 Female
Computer/Server Ports - Port 2	(x10) 3.5mm Female
Local Console Ports - Port 1	HD15 Female
Local Console Ports - Port 2	(x2) USB A Female

Local Console Ports - Port 3	(x2) MiniDIN6 Female (via included PS/2 to USB adapter cable)
Local Console Ports - Port 4	(x2) 3.5mm Female
WARRANTY	
Product Warranty Period (U.S., Canada & Puerto Rico)	1-year limited warranty

Related Items

Optional Products

Product Type	Related Model	Description	Qty.
Cables and Accessories	P312-006	6-ft. Mini-Stereo Dubbing Cord (3.5mm M/M)	-
Cables and Accessories	P312-010	10-ft. Mini-Stereo Dubbing Cord (3.5mm M/M)	-
Cables and Accessories	U022-006	6-ft. USB2.0 A/B Gold Device Cable (A Male to B Male)	-
Cables and Accessories	U022-010	10-ft. USB2.0 A/B Gold Device Cable (A Male to B Male)	-
Cables and Accessories	P756-010	10-ft. VGA/USB/Audio Combo Cable Kit for B006-VUA4-K-R KVM Switch	-
Cables and Accessories	P757-010	10-ft. VGA/PS2/Audio Combo Cable Kit for B006-VUA4-K-R KVM Switch	-

More information, including related products, owner's manuals, and additional technical specifications, can be found online at www.tripplite.com/en/products/model.cfm?txtModelID=4479.

Copyright © 2011 Tripp Lite. All rights reserved. All trademarks are the sole property of their respective owners. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Photos may differ slightly from final products.